



**Critical**  
manufacturing  
an ASM PT company

# Material Reservation Mode

11.0

March 2026

## DOCUMENT ACCESS

Public

## DISCLAIMER

The contents of this document are under copyright of Critical Manufacturing S.A. it is released on condition that it shall not be copied in whole, in part or otherwise reproduced (whether by photographic, or any other method) and the contents therefore shall not be divulged to any person other than that of the addressee (save to other authorized offices of his organization having need to know such contents, for the purpose for which disclosure is made) without prior written consent of submitting company.

# Material Reservation Mode

*Estimated time to read: 5 minutes*

When you are working with BOMs, and their Scope is Durables, Materials, Packing, or Weigh And Dispense, you will have to define whether the BOM Products include Material Reservations, and how Material Reservations are handled for the BOM Items.

Material Reservation is the process of allocating specific quantities of raw materials, components, or subassemblies from inventory to a specific production or work order. This ensures that those Materials are not consumed by other orders and are available when production begins.

The Material Reservation Mode property has three options to select from:

- Material Dependency
- None (default)
- Production Order

This tutorial will show you how to can use the Material Reservation Mode property in relation to the Material Dependency and Production Order options.

For both Material Dependency and Production Order you must ensure that you have your Critical Manufacturing MES structure configured which will allow you to set up these modes.

For the example scenario below, you will need to create:

- Steps
- Flows
- Products
- Materials
- BOMs
- Resources
- Services

For the purpose of this tutorial all new entities, including the ones above, were created and can be uploaded via the following Master Data files:

- [Material Dependency](#)
- [Production Order](#)

The provided Master Data files will allow you to undertake the paths and instructions provided below.

For more information, see [Manage BOM Items](#).

## Material Dependency

1. Create a **BOM** and set its Scope as Materials:

**Create New BOM**

1 CHANGE SET — 2 GENERAL DATA

**General Data**

Name: AA-BOM-01

Revision: Name can be automatically generated or you can enter a name of your choice

Description: AA-BOM-01

\* Type: General

Data Group:

**Information**

\* Scope: Materials

Product: Product

\* Base Quantity: 1

\* Units: Unit

Drawing: Drag file to upload or Browse File

Comments:

Cancel < Back Create

2. Select the section **BOM Items** and then select **Manage**:

**Manage BOM Items**

BOM ITEMS — SUBSTITUTES

AA-BOM-01 [A,2] / AA-BOM-01

**BOM Items**

PRODUCT	QTY
AA-Prod-01 [A] (AA-Prod-01)	1 Unit
AA-Prod-01	

**BOM Items Details**

\* Product: AA-Prod-01 [A]

Product Description: AA-Prod-01

\* Quantity: 1

Units: Unit

Location:

Position:

Named Position:

\* Source Step: AA-Step-Warehouse

Designator:

Assembly Step: AA-Step-Mixing

Comments:

Cancel < Back Next >

3. Be sure to enter the necessary information, and set the Material Reservation Mode property to Material Dependency:

**Manage BOM Items**

BOM ITEMS | SUBSTITUTES

AA-BOM-01 [A,Z] / AA-BOM-01

**BOM Items**

PRODUCT	QTY
AA-Prod-01 [A] (AA-Prod-01)	1 Unit
AA-Prod-01	

Source Step: AA-Step-warehouse

Designator:

Assembly Step: AA-Step-Mixing

Logical Flow Path:

Browse

Reference:

Product Mix Allowed:

Material Reservation Mode: Material Dependency

Condition

Characteristic: Browse

Value:

Comments:

Cancel < Back Next >

4. Define the **BOMContext** Smart Table by adding the **Step** when the **BOM** will be used, and the other necessary information:

**+ Add BOM Context Record(s)**

BOMContext (Active)

Record(s)

**Record #1**  
Step: AA-Step-Mixing | BOM: AA-BOM-01 | AssemblyType: AutomaticAtTrackOut | TrackInCheckMode: None | Trac

**BOM Context**

Step: AA-Step-Mixing

Logical Flow Path: Browse

Product: Product

Product Group: Product Group

Flow: Flow

Material: Material

Production Order: Production Order

BOM: AA-BOM-01

Assembly Type: Automatic At Track Out

Track-In Check Mode: None


Track-Out Losses Mode: Before Assembly

Weigh And Dispense Mode:


Comments:

Cancel Add

5. Attach your consumable **Material** as shown below:



6. Confirm the information and select **Attach**:



7. Go to the **Dependencies** section, select **Manage**, and select the **To** tab if you are creating the dependency from the main **Material** point of view:

**Manage Material Dependencies**

FROM TO

■ AA-Mat-02 (Queued) / # AA-Prod-02 [A] (AA-Prod-02) / ● AA-Step-Mixing / 10 Unit

**Dependencies**

- AA-Mat-01

**Material Dependency Details**

- \* From Material: AA-Mat-01
- \* From Step: AA-Step-Mixing
- From Flow Path: AA-Flow-Production [A] | AA-Step-Mixing
- Flow Path: AA-Flow-Production [A] > AA-Step-Mixing
- To Material: AA-Mat-02
- \* To Step: AA-Step-Mixing
- To Flow Path: AA-Flow-Production [A] | AA-Step-Mixing
- Flow Path: AA-Flow-Production [A] > AA-Step-Mixing

Comments:

Cancel Update

8. Complete the necessary information and make sure the System State property is set to Closed:

**Manage Material Dependencies**

FROM TO

■ AA-Mat-02 (Queued) / # AA-Prod-02 [A] (AA-Prod-02) / ● AA-Step-Mixing / 10 Unit

**Dependencies**

- AA-Mat-01

**Material Dependency Details**

- \* To Step: AA-Step-Mixing
- To Flow Path: AA-Flow-Production [A] | AA-Step-Mixing
- Flow Path: AA-Flow-Production [A] > AA-Step-Mixing
- From Quantity:
- From Units: Units
- To Quantity:
- To Units: Units
- System State: Closed
- Comment:

Comments:

Cancel Update

**Note**

If the System State property is set to Open, the system will return the following error when you try to Track-In:

Dispatch and Track-In Material

RESOURCE — BOM — RESULTS

AA-Mat-02 (Queued) / AA-Prod-02 [A] (AA-Prod-02) / AA-Step-Mixing / 10 Unit

**!** The object AA-Mat-02 of type Material has dependencies on object AA-Mat-01 of type Material.

Comments:

Cancel < Back Next > Track-In

9. You can now Dispatch and Track-In your main **Material** and verify the **BOM** information:

Dispatch and Track-In Material

RESOURCE — BOM

AA-Mat-02 (Queued) / AA-Prod-02 [A] (AA-Prod-02) / AA-Step-Mixing / 10 Unit

AA-BOM-01 [A] (AutomaticAtTrackOut) / Units: Unit


BOM

ITEM	LOCATION	POSITION	PRODUCT	PRODUCT DESCRIPT...	STEP	QUANTITY	REFERENCE	PRODUCT MIX	DISCRETE	REQUIRED QTY.	CURRENT QTY.	DELTA	
1			AA-Prod-01 [A]	AA-Prod-01	AA-Step-Warehous	1 Unit	X	X	X	10 Unit	10 Unit	0 Unit	1 >

Rows per Page: 25 Page 1 of 1 (1 Records)


Comments:

Cancel < Back Track-In



10. Select **Track-In**.

11. When you then select **Track-Out**, the whole **Material** will be consumed.



## Production Order

1. Create a **BOM** and set its Scope as Materials:

**Create New BOM**

CHANGE SET — GENERAL DATA

**General Data**

Name: AAA-BOM-01

Revision: *Name can be automatically generated or you can enter a name of your choice*

Description: AAA-BOM-01

\* Type: General

Data Group:

**Information**

\* Scope: Materials

Product: Product

\* Base Quantity: 1

\* Units: Unit

Drawing: [Drag files to upload](#) or [Browse Files](#)

Comments:

Cancel < Back Create

2. Select the section **BOM Items** and then select **Manage**:

**Manage BOM Items**

BOM ITEMS — SUBSTITUTES

AAA-BOM-01 [A.1] / AAA-BOM-01

**BOM Items**

PRODUCT	QTY
AAA-Prod-01 [A] (AAA-Prod-01)	1 Unit
No Position	

**BOM Items Details**

\* Product: AAA-Prod-01 [A]

Product Description: AAA-Prod-01

\* Quantity: 1

Units: Unit

Location:

Position:

Named Position:

\* Source Step: AAA-Step-Warehouse

Designator:

Assembly Step: AAA-Step-Mixing

Comments:

Cancel < Back Next >

3. Be sure to enter the necessary information, and set the Material Reservation Mode property to Production Order:

**Manage BOM Items**

BOM ITEMS / SUBSTITUTES

AAA-BOM-01 [A:1] / AAA-BOM-01

PRODUCT	QTY
AAA-Prod-01 [A] (AAA-Prod-01) <i>No Position</i>	1 Unit

Named Position:

\* Source Step: AAA-Step-Warehouse

Designator:

Assembly Step: AAA-Step-Mixing

Logical Flow Path:

Reference:

Product Mix Allowed:

\* Material Reservation Mode: Production Order

Condition

Characteristic:

Value:

Comments:

4. Define the **BOMContext** Smart Table by adding the **Step** when the **BOM** will be used, and the other necessary information:

**Add BOM Context Record(s)**

BOMContext (Active)

Record(s)	BOM Context
Record #1 Step: AAA-Step-Mixing   BOM: AAA-BOM-01   AssemblyType: AutomaticAtTrackOut   TrackInCheckMode: None   Tr	<p>* Step: AAA-Step-Mixing</p> <p>Logical Flow Path: <input type="text"/> <input type="button" value="Browse"/></p> <p>Product: <input type="text"/></p> <p>Product Group: <input type="text"/></p> <p>Flow: <input type="text"/></p> <p>Material: <input type="text"/></p> <p>Production Order: <input type="text"/></p> <p>* BOM: AAA-BOM-01</p> <p>* Assembly Type: Automatic At Track Out</p> <p>Track-In Check Mode: None</p> <p>Track-Out Losses Mode: Before Assembly</p> <p>Weigh And Dispense Mode: <input type="text"/></p>

Comments:

5. Create a **Production Order** with the **Product** to be produced and all the other necessary information:

**Create Production Order**

GENERAL DATA

**General Data**

Name: AAA-ProductionOrder

Description: AAA-ProductionOrder

\* Type: General

System State: Created

Data Group:

\* System State: Created

**Information**

\* Order Number: 1

Order Line:

Owner Role:

Customer: Business Partner

Facility: Facility

\* Product: AAA-Prod-021A1

Comments:

Cancel Create

**Create Production Order**

GENERAL DATA

\* Product: AAA-Prod-02[A]

\* Flow Path: AAA-Flow-Production [A] **AAA-Step-Mixing**

Browse

Flow Path: AAA-Flow-Production [A] > AAA-Step-Mixing

\* Quantity: 10

\* Units: Unit

\* Under Delivery Tolerance (%): 0 Minimum Quantity: 10

\* Over Delivery Tolerance (%): 0 Maximum Quantity: 10

Product Yield (%): 100

Yield Adjusted Quantity: 10

**Scheduling**

\* Due Date: 06/30/2025 04:31 PM


\* Priority: 5

Planned Start Date: MM/dd/yyyy HH:mm PP


Comments:

Cancel Create


6. On the top ribbon of your **Production Order**, select **Release**:




7. Enter the needed dates and select **Release**:




8. In the **Production Order**, select the **Materials** section followed but the **Assign** button on the top ribbon to assign your main **Material**:



9. Select **Assign** and your **Production Order** will have the main **Material** assigned to it:




10. Now, attach your consumable **Material** as shown below:




**Note**

This step is only needed because in this example we set the assembly Type of the BOM as Automatic at Track Out.

11. Next, in the **Production Order**, you will need to assign the consumption **Material** and then select **Assign**:



12. At this point, you can see your consumption **Material** and production information in the **Materials** section of your **Production Order**:



13. You can now Dispatch and Track-In your main **Material** and verify the BOM information:

Dispatch and Track-In Material

RESOURCE — BOM

AAA-Mat-02 (Queued) / AAA-Prod-02 [A] (AAA-Prod-02) / AAA-Step-Mixing / 10 Unit

AAA-BOM-01 [A] (AutomaticAtTrackOut) / Units: Unit

BOM

ITEM	LOCATION	POSITION	PRODUCT	PRODUCT DESCRPT...	STEP	QUANTITY	REFERENCE	PRODUCT MIX	DISCRETE	REQUIRED QTY.	CURRENT QTY.	DELTA
1			AAA-Prod-01 [A]	AAA-Prod-01	AAA-Step-Warehou	1 Unit	✗	✗	✗	10 Unit	10 Unit	0 Unit

Comments:

Cancel < Back Track-In

Dispatch and Track-In Material

RESOURCE — BOM

AAA-Mat-02 (Queued) / AAA-Prod-02 [A] (AAA-Prod-02) / AAA-Step-Mixing / 10 Unit

AAA-BOM-01 [A] (AutomaticAtTrackOut) / Units: Unit

Consumable Feed: AAA-Feeder-01

< AAA-Prod-01

MATERIAL	PRODUCT	STEP	PRIMARY QTY.	EXPIRATION DATE
AAA-Mat-01	AAA-Prod-01 [A]	AAA-Step-Warehouse	10 Unit	

Comments:

Cancel < Back Track-In

14. Select **Track-In**.

15. When you then select **Track-Out**, the whole **Material** will be consumed, as can be seen in the **Production Order**:

AAA-ProductionOrder

Refresh Edit Restrict Cancel Change Assign Reassign Create Material More

General Production Order Material Actions

AAA-ProductionOrder (Active)

PRODUCTION ORDER STEPS

MATERIALS

ACTIVE ACCOUNTS TO Search


MATERIAL	ACTIVE	ACCOUNTS TO	STATUS	PRODUCT	PRODUCT DESCRIPTION	QUANTITY	UNITS	FACILITY	STEP
AAA-Mat-02	✓	✓	In Progress	AAA-Prod-02 [A]	AAA-Prod-02	10	Unit	AAA-Facility	AAA-Step-Mixing

Comments:

Rows per Page: 25 Page 1 of 1 (1 Records)

**Warning**

If the consumable Material is not assigned to the Production Order, the system will return an error. This error is due to the dependency that is defined in the BOM which is used in the Production Order:



The screenshot shows the SAP Track-Out Material interface. At the top, there is a blue header with the title "Track-Out Material" and a help icon. Below the header, there are tabs for "RESOURCE STATE" and "RESULTS". The breadcrumb navigation shows the path: "AAA-Mat-02 (InProcess) / AAA-Prod-02 [A] (AAA-Prod-02) / AAA-Step-Mixing / 10 Unit". The main content area displays a red error message: "There was no Material of Product AAA-Prod-01 found in the Consumable Feeds of Resource AAA-Mixer-01". At the bottom of the interface, there is a "Comments:" field and a set of navigation buttons: "Cancel", "< Back", "Next >", and "Track-Out".



# Legal Information

## **Disclaimer**

The information contained in this document represents the current view of Critical Manufacturing on the issues discussed as of the date of publication. Because Critical Manufacturing must respond to changing market conditions, it should not be interpreted to be a commitment on the part of Critical Manufacturing, and Critical Manufacturing cannot guarantee the accuracy of any information presented after the date of publication. This document is for informational purposes only.

Critical Manufacturing makes no warranties, express, implied or statutory, as to the information herein contained.

## **Confidentiality Notice**

All materials and information included herein are being provided by Critical Manufacturing to its Customer solely for Customer internal use for its business purposes. Critical Manufacturing retains all rights, titles, interests in and copyrights to the materials and information herein. The materials and information contained herein constitute confidential information of Critical Manufacturing and the Customer must not disclose or transfer by any means any of these materials or information, whether total or partial, to any third party without the prior explicit consent by Critical Manufacturing.

## **Copyright Information**

All title and copyrights in and to the Software (including but not limited to any source code, binaries, designs, specifications, models, documents, layouts, images, photographs, animations, video, audio, music, text incorporated into the Software), the accompanying printed materials, and any copies of the Software, and any trademarks or service marks of Critical Manufacturing are owned by Critical Manufacturing unless explicitly stated otherwise. All title and intellectual property rights in and to the content that may be accessed through use of the Software is the property of the respective content owner and is protected by applicable copyright or other intellectual property laws and treaties.

## **Trademark Information**

Critical Manufacturing is a registered trademark of Critical Manufacturing.

All other trademarks are property of their respective owners.